

PRODUCT-DETAILS

# PSTX720-600-70

## PSTX720-600-70 Softstarter - 720 A - 208 ... 600 V AC



### General Information

Global Commercial Alias	PSTX720-600-70
Extended Product Type	PSTX720-600-70
Product ID	1SFA898118R7000
ABB Type Designation	PSTX720-600-70
EAN	7320500510384
Catalog Description	PSTX720-600-70 Softstarter - 720 A - 208 ... 600 V AC

### Long Description

The softstarter PSTX720-600-70 has a rated maximum operational current of 720 A with an operating voltage span from 208...600 V AC. The rated control voltage is between 100...250 V AC at 50/60 Hz. PSTX features a three-phase control soft start and stop through a voltage or a torque ramp. It has built-in bypass for easy installation and energy saving. A RUN, TOR and Event signal is available from relay outputs in NO (normally open state). The PSTX has functions such as current limit, kickstart, analog output, EOL, motor heating and pump cleaning. PSTX also features features jog, braking, stand-still brake, diagnostics, sequence start and emergency/fire pump mode as standard. To interact with PSTX, it has a detachable full graphic display with IP66 and 4x outdoor rating. There are four ways to communicate with PSTX. It can be done by hardwire inputs Start/Stop/Reset of fault, and by three programmable digital inputs. Another popular option is the built-in Fieldbus communication Modbus RTU and incl optional ANYBUS modules with every major protocol such as for example Profinet, Profibus, Modbus TCP, Ethernet IP and others. Another way to communicate with PSTX is to use an external adaptor and a Fieldbus plug. PSTX is the complete alternative for any motor starting application. It's suitable for medium to large-sized three-phase motors with nominal currents from 30...1250 A inline connection or 52...2160 A inside delta connection. Typical applications are, for example, pumps, fans, compressors, and conveyors.

### Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85371091

## Popular Downloads

Data Sheet, Technical Information	1SFC132012C0201
Instructions and Manuals	1SFC132081M0201
CAD Dimensional Drawing	2CDC001079B0201
Wiring Diagram	N/A

## Dimensions

Product Net Width	435 mm
Product Net Height	493 mm
Product Net Depth / Length	369 mm
Product Net Weight	46.5 kg

## Technical

Rated Operational Voltage	208 ... 600 V AC
Rated Control Supply Voltage (U <sub>s</sub> )	100 ... 250 V AC
Rated Control Circuit Voltage (U <sub>c</sub> )	24 V DC
Rated Frequency (f)	50/60 Hz Main Circuit 50 / 60 Hz
Rated Operational Power - In-Line Connection (P <sub>e</sub> )	(230 V) 200 kW (400 V) 400 kW (500 V) 500 kW
Rated Operational Current - In-Line Connection (I <sub>e</sub> )	720 A
Rated Operational Power - Inside Delta Connection	at 230 V 355 kW at 400 V 710 kW at 500 V 880 kW
Rated Operational Current - Inside Delta Connection	1247 A
Service Factor Percentage	100 %
Overload Protection	Built-in electronic overload protection
Integrated Electronic Overload	Yes
Adjustable Rated Motor Current I <sub>e</sub>	30 ... 100 %
Starting Capacity at Maximum Rated Current I <sub>e</sub>	4xI <sub>e</sub> for 10s
Ramp Time	1 ... 120 second [unit of time]
Initial Voltage During Start	10 ... 99 %
Step Down Voltage Special Ramp	100 ... 10 %
Current Limit Function	1.5 ... 7.5 xI <sub>e</sub>
Switch for Inside Delta Connection	Yes
Run Signal Relay	Yes

By-pass Signal Relay	Yes
Fault Signal Relay	Yes
Overload Signal Relay	Yes
Analog Outputs	0...10 V, 0...20 mA, 4...20 mA
Signal Indication Ready to Start/Standby ON (LED)	Green
Signal Indication Running R (LED)	Green
Signal Indication Protection (LED)	Yellow
Signal Indication Fault (LED)	Red
Communication	Modbus-RTU; Modbus-TCP; Ethernet-IP; EtherCAT; DeviceNet; CANopen; Profibus; Profinet; BACnet-IP; BACnet-MSTP
Degree of Protection	IP00
Terminal Type	Main Circuit: Bars
Connecting Capacity Control Circuit	Rigid 1 x 2.5 mm <sup>2</sup>
Connecting Capacity Supply Circuit	Rigid 1 x 2.5 mm <sup>2</sup>
Tightening Torque	Main Circuit 45 N·m
Product Main Type	PSTX720
Function	<ul style="list-style-type: none"> <li>Auto phase sequence detection</li> <li>Automatic restart</li> <li>Current limit</li> <li>Current limit ramp</li> <li>Dual current limit</li> <li>Dynamic brake</li> <li>Electricity metering</li> <li>Electronic overload Time-to-cool</li> <li>Emergency mode</li> <li>Event log</li> <li>Full voltage start</li> <li>Jog with slow speed, forward and reverse</li> <li>Keypad password</li> <li>Kick start</li> <li>Limp mode with two-phase motor control if one set of thyristors is shorted</li> <li>Motor heating</li> <li>Pre-start function</li> <li>Pump cleaning</li> <li>Real time clock</li> <li>Sequence start</li> <li>Soft start with torque control</li> <li>Soft start with voltage ramp</li> <li>Soft stop with torque control</li> <li>Soft stop with voltage ramp</li> <li>Stand still brake</li> <li>Start reverse (external contactors)</li> <li>Thyristor runtime measurement</li> <li>Torque limit</li> <li>Voltage sags detection</li> </ul>
Protection Function	<ul style="list-style-type: none"> <li>Bypass open protection; Current imbalance protection; Current underload protection; Dual overload (separate overload for start and run); Earth fault protection / ground fault protection; Electronic overload protection, EOL; Extension IO failure protection; Fieldbus failure protection; HMI failure protection; Locked rotor protection; Max number of starts/hour; Over voltage protection; Phase reversal protection; Power factor underload protection; PT-100 connection; PTC connection; Too long current limit protection; Too long start time protection; Under voltage protection; User defined protection; Voltage imbalance protection</li> </ul>
Warning Details	<ul style="list-style-type: none"> <li>Current imbalance warning; Current underload warning; Electronic overload Time-to-trip; EOL warning; Faulty fan warning; Locked rotor warning; Motor runtime limit warning; Over voltage warning; Phase loss warning (for standby); Power factor underload warning; Short circuit warning (for Limp mode); THD(U) - Total Harmonic Distortion warning; Thyristor overload warning (SCR); Under voltage warning; Voltage imbalance warning</li> </ul>

---

**Technical UL/CSA**


---

Maximum Operating Voltage UL/CSA	Main Circuit 600 V
Tightening Torque UL/CSA	Main Circuit 398.3

---

## Environmental

Ambient Air Temperature	Operation -25 ... +60 °C Storage -40 ... +70 °C
Degree of Protection	IP00
RoHS Information	2CMT005210
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment

---

## Certificates and Declarations

CQC Certificate	CN: CQC2015010304830300 / SE: CQC2015010304830295
Declaration of Conformity - CCC	CN: 2020980304001095 / SE: 2020980304001491
Declaration of Conformity - CE	2CMT005209

---

## Container Information

Package Level 1 Width	600 mm
Package Level 1 Depth / Length	616 mm
Package Level 1 Height	800 mm
Package Level 1 Gross Weight	58.5 kg
Package Level 1 EAN	7320500510384
Package Level 1 Units	box 1 piece

---

## Classifications

Object Classification Code	Q
ETIM 7	EC000640 - Soft starter
ETIM 8	EC000640 - Soft starter
ETIM 9	EC000640 - Soft starter
eClass	V11.0 : 27370907
UNSPSC	39121521
IDEA Granular Category Code (IGCC)	4740 >> Soft starter

---

## Accessories

Identifier	Description	Type	Quantity	Unit Of Measure
1SDA013956R1	KIT FC CuAI 3x185mm2 T6 800-S6 800 6pcs	KIT FC CuAI 3x185mm2 T6 800-S6 800 6pcs	1	piece
1SDA054988R1	KIT FC CuAI 1x185mm2 T4 3pcs	KIT FC CuAI 1x185mm2 T4 3pcs	1	piece
1SDA055020R1	KIT FC CuAI 1x240mm2 T5 400 3pcs	KIT FC CuAI 1x240mm2 T5 400 3pcs	1	piece
1SDA023380R1	KIT FC CuAI 2x240mm2 T6 630-S6 630 3pcs	KIT FC CuAI 2x240mm2 T6 630-S6 630 3pcs	1	piece
1SFN074810R1000	LX205 Terminal Extension	LX205	1	piece
1SFN075410R1000	LX370 Terminal Extension	LX370	1	piece
1SFN075710R1000	LX460 Terminal Extension	LX460	1	piece
1SFN074307R1000	LW110 Terminal Enlargement	LW110	1	piece
1SFN074807R1000	LW205 Terminal Enlargement	LW205	1	piece
1SFN075407R1000	LW370 Terminal Extension	LW370	1	piece
1SFN075707R1000	LW460 Terminal Enlargement	LW460	1	piece
1SFN076107R1000	LW750 Terminal Enlargement	LW750	1	piece
1SFN124801R1000	LT205-30C Terminal Shroud	LT205-30C	1	piece
1SFN124803R1000	LT205-30L Terminal Shroud	LT205-30L	1	piece
1SFN125401R1000	LT370-30C Terminal Shroud	LT370-30C	1	piece
1SFN125403R1000	LT370-30L Terminal Shroud	LT370-30L	1	piece
1SFN125406R1000	LT370-30D Terminal Shroud	LT370-30D	1	piece
1SFN125701R1000	LT460-AC Terminal shroud	LT460-AC	1	piece
1SFN125703R1000	LT460-AL Terminal shroud	LT460-AL	1	piece
1SFN126101R1000	LT750-AC Terminal shroud	LT750-AC	1	piece
1SFN126103R1000	LT750-AL Terminal shroud	LT750-AL	1	piece
1SFA899314R1001	PSCA-1 USB cable	PSCA-1	1	piece
1SFA899300R1001	AB-PROFIBUS-1 Communication Module	AB-PROFIBUS -1	1	piece
1SFA899300R1002	AB-DEVICENET-1 Communication Module	AB- DEVICENET-1	1	piece
1SFA899300R1003	AB-MODBUS-RTU-1 Communication Module	AB-MODBUS- RTU-1	1	piece
1SFA899300R1006	AB-ETHERNET-IP-2 Communication Module	AB- ETHERNET-IP -2	1	piece
1SFA899300R1008	AB-MODBUS-TCP-2 Communication Module	AB-MODBUS- TCP-2	1	piece
1SFA899300R1010	AB-PROFINET-IO-2 Communication Module	AB-PROFINET -IO-2	1	piece
1SFA899300R1011	AB-BACNET-MSTP-1 Communication Module	AB-BACNET- MSTP-1	1	piece
1SFA899300R1012	AB-ETHERCAT-IP-2 Communication Module	AB- ETHERCAT-IP -2	1	piece
1SAJ611000R0101	DX111-FBP.0 IO-Module for UMC100 DI 24 VDC, supply 24VDC	DX111-FBP.0	1	piece
1SAJ622000R0101	DX122-FBP.0 IO-Module for UMC100 DI 110/230VAC, supply 24VDC	DX122-FBP.0	1	piece
1SFA896312R1002	PS-FBPA Fieldbus plug kit	PS-FBPA	1	piece

---

## Categories

---

Drives → Softstarters → Softstarters → PSTX Softstarters → PSTX720

Low Voltage Products and Systems → Control Products → Softstarters → Softstarters → PSTX Softstarters → PSTX720

